

Installation Guide



Safety Information - Read Before Installation

After choosing a suitable location that meets all the requirements of the safety information, install the unit following the steps overleaf.

- Carefully unpack all parts and check for damage or missing parts before commencing installation.
- Installation of this product must be carried out by a qualified electrical contractor.
- Luminaire is suitable for indoor locations only.
- Be sure to follow the steps in the order given.
- Shut off power at the fuse box or circuit breaker box.
- If necessary, remove old fixture and all mounting hardware from the junction box.
- The supply wires must be rated for at least 90°C

- This product must be installed in accordance with all applicable installation codes by a person familiar with the construction and operation of the product and the hazards involved.
- Ensure that the support for the luminaire is of sufficient structural strength and that any fixing screws do not interfere with the connecting cables.
- The light must be mounted on a non-flammable surface as a fixed luminaire, and is not suitable for portable use.
- The unit can get very hot during use. Ensure the unit has cooled before handling.
- Ensure adequate ventilation space is allowed between the unit and any object above, in front or to either side of the unit. Suggested minimum space is 19½" above and 19½" on all sides.
- To prevent tarnishing, it is advisable to wear gloves at all times when handling the product.

Care Instructions - Read Before Installation

- This box contains fragile and valuable goods that have been carefully packed. Please take utmost care in unpacking the parcel as damage can occur in this process.
- Please be sure you have received the correct number of boxes i.e. 1 of 2, 2 of 2 etc.
- Under no circumstances should the product be lifted out by the neck or light fitting.
- If you have received any damaged goods or are missing any part of your order, please contact our sales office as soon as possible

Recycling

- Recyclable packaging used, please consult with your local recycling centre for further information.
- Waste electrical products should not be disposed of with conventional household waste. Please recycle all parts when possible.

Cleaning Instructions

Brass - all types: Use a soft dry lint free cloth

Bronze, Nickel, Silver & Chrome: Use a dry cloth only, no chemical cleaners

Glass: We recommend using a strong alcohol such as isopropyl alcohol. Note: some modern cleaning solutions can contain chemicals that can leave a greasy film on glass.

Gilt Wood: Use a dry cloth only

Ceramic: Use a damp cloth only

Wood: Wax polish i.e. Antique wax

Alabaster: Dust with a soft brush or a clean dry cloth. Avoid water or water-based cleaners. Any marks that cannot be removed by dusting must be cleaned by a specialist.

Lacquered Furniture: Furniture polish

Crystal: Damp cloth


Card/Laminated Shades: Use a Feather duster only

Silk Shades: Gently tap to lift dust


Needlework: Dry-clean

- Any decorative parts made from other materials must be removed and cleaned separately to avoid damage - e.g. alabaster.


Tiverton Semi Flush Chandelier




1. Remove the top ring from the product.




2. Remove the grub screw from the ceiling rose and assemble to the top rod. Take caution to not damage the product.




3. Using the grub screw, secure the loop to the end of the threaded rod. Ensure all the components are secured tightly.




4. Using the bracket adapter, attach the bracket to the ceiling box.




5. Hook the loop onto the ceiling bracket. The ceiling rose should remain lowered to allow the product to be wired. Thread the cable up into the ceiling box.




6. Having identified the household wiring, connect the building supply and the product cables together in the wire connectors as shown above.




7. Secure the ceiling rose cup to the ceiling using the grub screw, ensuring it is tightly fitted



8. Attach the decorative glass to the top ring.



9. Reattach the top ring to the product.



10. Attach the decorative glass to the bottom of the product.

Français

1. Retirez l'anneau supérieur du produit.
2. Desserrez la vis sans tête afin de faire tomber la rosace.
3. À l'aide de la vis sans tête, fixez la boucle à l'extrémité de la tige filetée. Assurez-vous que tous les composants sont solidement fixés.
4. À l'aide de l'adaptateur de support, fixez le support au boîtier de plafond.
5. Accrochez la boucle sur le support de plafond. La rosace doit rester abaissée pour permettre le câblage du produit. Faites passer le câble dans le boîtier de plafond.
6. Après avoir identifié le câblage domestique, connectez les câbles d'alimentation du bâtiment et les câbles du produit ensemble dans les connecteurs de fils comme indiqué ci-dessus.
7. Fixez la rosace au plafond à l'aide de la vis sans tête, en vous assurant qu'elle soit bien fixée.
8. Fixez le verre décoratif à l'anneau supérieur.
9. Fixez à nouveau l'anneau supérieur au produit.
10. Fixez le verre décoratif sur la partie inférieure du produit.

Español

1. Retire el anillo superior del producto.
2. Afloja el tornillo prisionero para soltar el rosetón.
3. Con el tornillo prisionero, asegure el lazo al extremo de la varilla roscada. Asegúrese de que todos los componentes estén bien asegurados.
4. Usando el adaptador de soporte, fije el soporte a la caja del techo.
5. Enganche el lazo en el soporte de techo. El rosetón debe permanecer bajado para permitir el cableado del producto. Pase el cable hacia arriba en la caja del techo.
6. Una vez identificado el cableado de la casa, conecte el suministro del edificio y los cables del producto juntos en los conectores de cables como se muestra arriba.
7. Asegura el rosetón del techo al techo con el tornillo prisionero, asegurándose de que quede bien ajustado.
8. Coloque el vidrio decorativo en el anillo superior.
9. Vuelva a colocar el anillo superior en el producto.
10. Coloque el vidrio decorativo en la parte inferior del producto.

Deutsche

1. Nehmen Sie den oberen Ring vom Produkt ab.
2. Lösen Sie die Madenschraube, um die Deckenrosette abzusenken.
3. Befestigen Sie die Schlaufe mit der Madenschraube am Ende der Gewindestange. Stellen Sie sicher, dass alle Komponenten fest befestigt sind.
4. Befestigen Sie die Halterung mit dem Halterungsadapter an der Deckenbox.
5. Haken Sie die Schlaufe an der Deckenhalterung ein. Der Deckenbaldachin sollte abgesenkt bleiben, damit das Produkt verkabelt werden kann. Fädeln Sie das Kabel nach oben in die Deckendose.
6. Nach Identifikation der Hausstromverkabelung verbinden Sie die Gebäudeversorgung und die Produktkabel in den Leitungsverbindern wie oben gezeigt.
7. Befestigen Sie die Deckenrosette mit der Madenschraube an der Decke und stellen Sie sicher, dass sie fest sitzt.
8. Bringen Sie das dekorative Glas am oberen Ring an.
9. Bringen Sie den oberen Ring wieder am Produkt an.
10. Bringen Sie das dekorative Glas an der Unterseite des Produkts an.

Italiano

1. Rimuovi l'anello superiore dal prodotto.
2. Allentare il grano per far scendere il rosone.
3. Utilizzando il grano, fissare l'anello all'estremità dell'asta filettata. Assicurarsi che tutti i componenti siano fissati saldamente.
4. Utilizzando l'adattatore per staffa, fissare la staffa alla scatola del soffitto.
5. Agganciare l'anello alla staffa da soffitto. Il rosone deve rimanere abbassato per consentire il cablaggio del prodotto. Infilare il cavo nella scatola del soffitto.
6. Dopo aver individuato l'impianto elettrico domestico, collegare l'alimentazione dell'edificio ai cavi del prodotto nei connettori per cavi come mostrato sopra.
7. Fissare la calotta del rosone al soffitto usando il grano, assicurandosi che sia ben aderente.
8. Fissa il vetro decorativo all'anello superiore.
9. Fissa nuovamente l'anello superiore al prodotto.
10. Fissa il vetro decorativo alla parte inferiore del prodotto.