

Installation Guide



Safety Information - Read Before Installation

After choosing a suitable location that meets all the requirements of the safety information, install the unit following the steps overleaf.

- Carefully unpack all parts and check for damage or missing parts before commencing installation.
- Installation of this product must be carried out by a qualified electrical contractor.
- Luminaire is suitable for indoor locations only.
- Be sure to follow the steps in the order given.
- Shut off power at the fuse box or circuit breaker box.
- If necessary, remove old fixture and all mounting hardware from the junction box.
- The supply wires must be rated for at least 90°C

- This product must be installed in accordance with all applicable installation codes by a person familiar with the construction and operation of the product and the hazards involved.
- Ensure that the support for the luminaire is of sufficient structural strength and that any fixing screws do not interfere with the connecting cables.
- The light must be mounted on a non-flammable surface as a fixed luminaire, and is not suitable for portable use.
- The unit can get very hot during use. Switch the product off and allow to cool before handling or changing bulbs.
- Ensure adequate ventilation space is allowed between the unit and any object above, in front or to either side of the unit. Suggested minimum space is 19½" above and 19½" on all sides.
- To prevent tarnishing, it is advisable to wear gloves at all times when handling the product.

Care Instructions - Read Before Installation

- This box contains fragile and valuable goods that have been carefully packed. Please take utmost care in unpacking the parcel as damage can occur in this process.
- Please be sure you have received the correct number of boxes i.e. 1 of 2, 2 of 2 etc.
- Under no circumstances should the product be lifted out by the neck or light fitting.
- If you have received any damaged goods or are missing any part of your order, please contact our sales office as soon as possible


Recycling

- Recyclable packaging used, please consult with your local recycling centre for further information.
- Waste electrical products should not be disposed of with conventional household waste. Please recycle all parts when possible.


Cleaning Instructions

- Brass** - all types: Use a soft dry lint free cloth
- Bronze, Nickel, Silver & Chrome:** Use a dry cloth only, no chemical cleaners
- Glass:** We recommend using a strong alcohol such as isopropyl alcohol. Note: some modern cleaning solutions can contain chemicals that can leave a greasy film on glass.
- Gilt Wood:** Use a dry cloth only
- Ceramic:** Use a damp cloth only
- Wood:** Wax polish i.e. Antique wax
- Alabaster:** Dust with a soft brush or a clean dry cloth. Avoid water or water-based cleaners. Any marks that cannot be removed by dusting must be cleaned by a specialist.
- Lacquered Furniture:** Furniture polish
- Crystal:** Damp cloth
- Card/Laminated Shades:** Use a Feather duster only
- Silk Shades:** Gently tap to lift dust
- Needlework:** Dry-clean
- Any decorative parts made from other materials must be removed and cleaned separately to avoid damage - e.g. alabaster.


Swing Arm Wall Light Rod Kit




1. Straighten the product wiring, remove the grub screw and the backplate from the product.




2. Disconnect the inline connector. Plug the product into the plug set.




3. Attach the back plate and adapter bracket (2 gang box only) to the wall box.



4. Insert the cable cover rod into the recess at the bottom of the backplate. Ensure the cable is fed into the rod.




5. Reattach the product to the backplate by engaging the lower tabs, align with top ledge of back plate and secure with the grub screw.




6. Using the fixings provided secure the base of the rod as shown.

Swing Arm Wall Light Rod Kit




7. Fix the appropriate bulb into the lamp holder.




8. Attach the harp as shown.


Secure the shade with use of the decorative finial.



9. Plug the product into the main power supply.



10. Use the switch as necessary to turn the product on and off.



11. Manoeuvre the arm into the desired position.

Français

1. Redressez le câblage du produit, retirez la vis sans tête et la plaque arrière du produit.
2. Débranchez les connecteurs. Branchez le produit sur jeu de fiches.
3. Fixez la plaque arrière au mur à l'aide de fixations appropriées.
4. Insérez la tige du cache-câble dans le renforcement situé au bas de la plaque arrière. Veillez à ce que le câble soit introduit dans la tige.
5. Fixez à nouveau le produit sur la plaque arrière en engageant les languettes inférieures, alignez-les avec le rebord supérieur de la plaque arrière et fixez-les avec la vis sans tête.
6. À l'aide des fixations fournies, fixez la base de la tige comme indiqué.
7. Fixez l'ampoule appropriée sur le support de lampe.
8. Fixez la harpe tel qu'illustré. Sécurisez l'abat-jour à l'aide de l'embout décoratif.
9. Branchez le produit sur l'alimentation principale.
10. Si nécessaire, utilisez l'interrupteur pour allumer et éteindre le produit.
11. Manœuvrez le bras dans la position souhaitée.

Español

1. Enderece el cableado del producto, retire el tornillo sin cabeza y la placa posterior del producto.
2. Desconecte los conectores internos. Conecte el producto a la juego de enchufes.
3. Sujete la placa posterior a la pared con las fijaciones adecuadas.
4. Inserte la varilla de la cubierta del cable en el hueco que hay en la parte inferior de la placa posterior. Asegúrese de que el cable entra en la varilla.
5. Vuelva a colocar el producto en la placa posterior mediante las pestañas inferiores, alinéelo con el borde superior de la placa posterior y asegúrelo con el tornillo sin cabeza.
6. Utilice los elementos de fijación suministrados para sujetar la base de la varilla como se indica en la ilustración.
7. Fije la bombilla adecuada en el portalámparas.
8. Coloque el arpa como se muestra. Fíjelo la pantalla de la lámpara con el pináculo decorativo.
9. Conecte el producto a la fuente de alimentación principal.
10. Utilice el interruptor según sea necesario para encender y apagar el producto.
11. Coloque el brazo en la posición que desee.

Deutsche

1. Ziehen Sie die Kabel des Produktes glatt, entfernen Sie den Gewindestift und die Rückwand vom Produkt.
2. Trennen Sie die Inline-Stecker. Schließen Sie das Gerät an das Steckersatz.
3. Befestigen Sie die Rückwand mit geeigneten Befestigungen an der Wand.
4. Setzen Sie das Kabelabdeckungsrohr in die Aussparung an der Unterseite der Rückplatte ein. Führen Sie das Kabel in das Rohr ein.
5. Montieren Sie das Produkt wieder an der Rückwand, indem Sie die unteren Schlaufen einstellen, richten Sie es mit dem oberen Rand der Rückwand aus und sichern Sie es mit dem Gewindestift.
6. Sichern Sie wie abgebildet den unteren Teil des Rohrs mit den mitgelieferten Befestigungen.
7. Setzen Sie die entsprechende Glühbirne in die Lampenfassung ein.
8. Bringen Sie die Harfe wie abgebildet an. Sichern den Lampenschirm Sie sie mit der dekorativen Zierspitze.
9. Schließen Sie das Gerät an das Stromnetz an.
10. Schalten Sie das Gerät bei Bedarf mit dem Schalter ein und aus.
11. Manövrieren Sie den Hebel in die gewünschte Position.

Italiano

1. Districare il circuito elettrico del prodotto, rimuovere il grano e la piastra posteriore dal prodotto.
2. Scollegare i connettori volanti. Collegare il prodotto alla set di connettori.
3. Fissare la piastra posteriore alla parete utilizzando sostegni adatti.
4. Inserire l'asta di copertura del cavo nell'incavo nella parte inferiore della piastra posteriore. Assicurarsi che il cavo sia inserito all'interno dell'asta.
5. Riattaccare il prodotto alla piastra posteriore servendosi delle linguette inferiori, allineandolo con la mensola superiore della piastra posteriore e fissandolo con il grano.
6. Utilizzando i fissaggi forniti, fissare la base dell'asta come mostrato.
7. Montare la lampadina appropriata nel portalampada.
8. Fissa l'arpa come illustrato. Fissare il paralume con l'uso dell'elemento decorativo.
9. Collegare il prodotto alla rete elettrica.
10. Usare l'interruttore a seconda delle necessità per accendere e spegnere il prodotto.
11. Posizionare il braccio nella posizione che desideri.